



## Maya2000Pro Series Spectrometers Installation and Operation Manual



For Products: Maya 2000Pro and  
Maya2000Pro-NIR  
Document: 020-00000-000-02-201603b

A HALMA COMPANY

## AMERICAS & WORLD HEADQUARTERS

---

**Phone:** +1 727-733-2447  
**Fax:** +1 727-733-3962

**Sales:** info@oceanoptics.com  
**Orders:** orders@oceanoptics.com  
**Support:** techsupport@oceanoptics.com

**Ocean Optics, Inc.**  
830 Douglas Ave.  
Dunedin, FL 34698  
USA

**Manufacturing & Logistics**  
4301 Metric Dr.  
Winter Park, FL 32792  
USA

## EUROPE, MIDDLE EAST & AFRICA

---

**Phone:** +31 26-319-0500  
**Fax:** +31 26-319-0505  
**Email:** info@oceanoptics.eu

Germany : +49 711-341696-0  
UK : +44 1865-811118  
France : +33 442-386-588

**Sales & Support**  
Geograaf 24  
6921 EW Duiven  
The Netherlands

**Manufacturing & Logistics**  
Maybachstrasse 11  
73760 Ostfildern  
Germany

## ASIA

---

**Phone:** +86 21-6295-6600  
**Fax:** +86 21-6295-6708  
**Email:** asiasales@oceanoptics.com

Japan & Korea: +82 10-8514-3797

**Ocean Optics Asia**  
666 Gubei Road  
Kirin Tower Suite 601B  
Changning District  
Shanghai  
PRC, 200336

---

**www.oceanoptics.com**

---

### **Copyright © 2009 Ocean Optics, Inc.**

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted, by any means, electronic, mechanical, photocopying, recording, or otherwise, without written permission from Ocean Optics, Inc.

### **Trademarks**

All products and services herein are the trademarks, service marks, registered trademarks or registered service marks of their respective owners.

### **Limit of Liability**

Every effort has been made to make this manual as complete and as accurate as possible, but no warranty or fitness is implied. The information provided is on an "as is" basis. Ocean Optics, Inc. shall have neither liability nor responsibility to any person or entity with respect to any loss or damages arising from the information contained in this manual.

---

# Table of Contents

About This Manual.....	iii
Document Purpose and Intended Audience.....	iii
What's New in this Document .....	iii
Document Summary.....	iii
Product-Related Documentation .....	iii
Upgrades.....	iv
<b>Chapter 1: Introduction .....</b>	<b>1</b>
Product Overview .....	1
Models.....	2
Features .....	2
System Requirements .....	3
EEPROM Utilization .....	3
About OceanView Software.....	3
Sampling System Overview.....	3
How Sampling Works.....	3
Modular Sampling Accessories.....	4
Interface .....	4
Shipment Components .....	4
Other Accessories Available .....	5
Breakout Box .....	5
<b>Chapter 2: Installing the Maya2000Pro Series Spectrometers .....</b>	<b>7</b>
Overview .....	7
Maya2000Pro Series Installation .....	7
Configuring the Maya2000Pro Series Spectrometers .....	8
OceanView QE <i>Pro</i> Acquisition Controls .....	8
Connect Spectroscopic Accessories.....	10
<b>Chapter 3: Troubleshooting .....</b>	<b>13</b>
Overview .....	13
Maya2000Pro Series Spectrometers Connected to Computer Prior to Software Installation .....	13

Windows Operating Systems .....	13
Remove the Unknown Device from Windows Device Manager .....	13
Mac Operating Systems .....	14
Linux Operating Systems .....	14
<b>Appendix A: Calibrating the Wavelength of the Maya2000Pro Series Spectrometers.....</b>	<b>15</b>
Overview .....	15
About Wavelength Calibration .....	15
Calibrating the Spectrometer .....	16
Preparing for Calibration.....	16
Calibrating the Wavelength of the Spectrometer .....	16
Saving the New Calibration Coefficients: USB Mode .....	18
<b>Appendix B: Specifications.....</b>	<b>19</b>
Overview .....	19
How the Maya2000Pro Series Works .....	19
Maya2000Pro Series Components Table .....	20
Maya2000Pro Series Spectrometers Specifications .....	21
CCD Detector Specifications .....	21
Maya2000Pro Series Spectrometer Specifications .....	22
System Compatibility .....	23
30-Pin Accessory Connector Pinout .....	23
30-Pin Accessory Connector Pinout Diagram .....	24
30-Pin Accessory Connector – Pin Definitions and Descriptions.....	24
30-Pin J2 Accessory Connector - Part Numbers.....	26
<b>Index .....</b>	<b>27</b>

---

# About This Manual

## Document Purpose and Intended Audience

This document provides the user of a Maya2000Pro Series Spectrometer with instructions for setting up, calibrating and performing experiments with their spectrometer.

## What's New in this Document

This version of the *Maya2000Pro and Maya2000Pro-NIR Installation and Operation Manual* adds information for the shutter and interchangeable slits.

## Document Summary

Chapter	Description
Chapter 1: <a href="#">Introduction</a>	Contains descriptive information about the Maya2000Pro Series Spectrometers and how sampling works. It also provides a list of system requirements, interface options, and shipment components.
Chapter 2: <a href="#">Installing the Maya2000Pro Series</a>	Provides installation and configuration instructions.
Chapter 3: <a href="#">Troubleshooting</a>	Contains recommended steps to isolate and correct common problems.
Appendix A: <a href="#">Calibrating the Wavelength of the Maya2000Pro Series</a>	Provides instructions for calibrating the Maya2000Pro Series Spectrometers.
Appendix B: <a href="#">Specifications</a>	Contains technical specifications and connector pinouts for the Maya2000Pro Series Spectrometers.

## Product-Related Documentation

You can access documentation for Ocean Optics products by visiting our website at <http://www.oceanoptics.com>. Select *Technical Operating Instructions*, then choose the appropriate document from the available drop-down lists.

Document for...	Document Location
OceanView software	<a href="http://oceanoptics.com//wp-content/uploads/OceanViewIO.pdf">http://oceanoptics.com//wp-content/uploads/OceanViewIO.pdf</a>

Document for...	Document Location
SpectraSuite software	<a href="http://oceanoptics.com/wp-content/uploads/SpectraSuite.pdf">http://oceanoptics.com/wp-content/uploads/SpectraSuite.pdf</a>
HR-4 Breakout Box	<a href="http://oceanoptics.com/wp-content/uploads/HR-4-Breakout-Box.pdf">http://oceanoptics.com/wp-content/uploads/HR-4-Breakout-Box.pdf</a>
External triggering for firmware versions below 3.0	<a href="http://oceanoptics.com/wp-content/uploads/External-Triggering-Options.pdf">http://oceanoptics.com/wp-content/uploads/External-Triggering-Options.pdf</a>
External triggering for firmware versions 3.0 and above	<a href="http://oceanoptics.com/wp-content/uploads/External-Triggering-Options_Firmware3.0andAbove.pdf">http://oceanoptics.com/wp-content/uploads/External-Triggering-Options_Firmware3.0andAbove.pdf</a>

Ocean Optics offers a Glossary of spectroscopy terms to help you further understand your state-of-the-art products and how they function, located at: <http://oceanoptics.com/glossary/>.

## Upgrades

Occasionally, you may find that you need Ocean Optics to make a change or an upgrade to your system. To facilitate these changes, you must first contact Customer Support and obtain a Return Merchandise Authorization (RMA) number. Please contact Ocean Optics for specific instructions when returning a product.

Our 3-Year Warranty covers Ocean Optics miniature fiber optic spectrometers, light sources and sampling accessories – regardless of the application – from manufacturing defects. It also covers fibers and probes for a full 12 months: <http://oceanoptics.com/services/exclusive-3-year-warranty/>.

This comprehensive warranty ensures you of the highest level of craftsmanship and reliability for years to come. No other manufacturer offers such a solid guarantee of quality and reliability.

The Ocean Optics 3-Year Warranty applies to Ocean Optics equipment (excluding OEM configurations) purchased on or after July 1, 2010. The warranty covers parts and labor needed to repair manufacturing defects that occur during the warranty period. We also will cover the costs of shipping warranty-related repairs from our customers to Ocean Optics and from us to our customers.

## ISO Certification

Ocean Optics, the industry leader in miniature photonics, has been certified for ISO 9001:2008 certification applicable to the design and manufacture of electro-optical equipment since 2009.

### **WARNING**

**This is a Class A product. In a domestic environment this product may cause radio interference in which case the user may be required to take adequate measures.**

---

### **FCC COMPLIANCE**

**This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which the user will be required to correct the interference at his own expense.**

**WARNING:** The authority to operate this equipment is conditioned by the requirement that no modifications will be made to the equipment unless the changes or modifications are expressly approved by the manufacturer.

---





---

# Chapter 1

# Introduction

## Product Overview

The Ocean Optics Maya2000Pro Series Spectrometers have been engineered specifically for low light-level, UV-sensitive and other scientific applications such as fluorescence, DNA sequencing and Raman spectroscopy. These next-generation spectrometers have great quantum efficiency, high dynamic range, extreme sensitivity and excellent deep-UV (<190 nm) response.



### **Ocean Optics Maya2000Pro High-Sensitivity Fiber Optic Spectrometer**

The Maya2000Pro Series Spectrometers feature the Hamamatsu FFT-CCD back-thinned detector, which offers excellent performance characteristics. Because of their great native UV-response, FFT-CCD detectors do not require UV-sensitive coatings, eliminating batch-to-batch variations. Other performance advantages of this detector include great signal-to-noise characteristics, low dark current and good signal processing speed.

The Maya2000Pro Series' onboard module has 10 user-programmable digital I/O lines for interfacing to other equipment; and a pulse generator for triggering other devices. You can use the I/Os to flash a lamp, stop/start a process, and send a message/alarm during the spectrometer's integration period. The spectrometer's operating parameters can be controlled through software. In fact, wavelength calibration coefficients unique to each spectrometer are programmed into a memory chip right on the spectrometer.

The Maya2000Pro Series' high-speed electronics have been designed for considerable flexibility in connecting to various modules and external interfaces, including PCs, PLCs and other embedded controllers, through USB 2.0 communications. Its USB 2.0 interface enables full spectral scans into memory every 7 milliseconds.

An optional internal shutter is available on custom-configured spectrometers (INTERNAL-SHUTTER-LRG-BENCH). This makes it easier to take dark measurements and when you need fast integration times with the best possible signal. This optional feature is also recommended for probe-based or emissive measurements where it is difficult to introduce a shutter into the optical path. The shutter can be added to an existing Maya spectrometer for an extra charge.

Replaceable slits are offered for added convenience. ). Deep UV option includes purge port.

The Maya2000Pro Series Spectrometers operate via USB interface.

## Models

The Maya2000Pro Series Spectrometers consist of the Maya2000 Pro and the Maya2000Pro-NIR. The Maya2000 has been discontinued. While these spectrometers have similar performance for most parameters, the Maya2000Pro -NIR offers high sensitivity in the NIR range while the Maya2000Pro offers high sensitivity in the UV range. See [Maya2000Pro Series Spectrometers Specifications](#) for a side-by-side comparison.

## Features

- Hamamatsu S10420 (Maya2000Pro), or Hamamatsu S11510 (Maya2000Pro-NIR) Detector
  - Peak QE: 75% for Maya2000 Pro; 85% for Maya2000Pro-NIR
  - Back-thinned for good UV sensitivity
  - MPP operation for low noise
- Spectrometer Design
  - Symmetrical Crossed Czerny Turner
  - 101mm focal length
  - 14 grating options, including the HC-1 composite grating for coverage from 175-1100 nm (additional charge)
  - 6 slit widths
  - Interchangeable slits
- Kensington<sup>®</sup> security slot
- Optional shutter for dark measurements requiring a fast integration time and good throughput – Specify when ordering
- Electrical Performance
  - 16 bit, 500KHz A/D converter
  - Integration times: 6ms to 5sec for Maya2000 Pro
- Embedded microcontroller allows programmatic control of all operating parameters and standalone operation
  - USB 2.0 480Mbps (high-speed) & 12Mbps (full speed)
  - Multiple communication standards for digital accessories (SPI, I2C)
- Onboard Pulse Generator

- 2 programmable strobe signals for triggering other devices
- Software control of nearly all pulse parameters
- Onboard GPIO
  - 10 user-programmable digital I/Os
- EEPROM storage for
  - Wavelength Calibration Coefficients
  - Linearity Correction Coefficients
  - Absolute Irradiance Calibration (optional)
- Plug-n-play interface for PC applications
- 30-pin connector for interfacing to external products
- CE certification

## System Requirements

You can use the Maya2000Pro Series' USB connectivity with any computer that meets the requirements for the spectrometer operating software being used (Windows 98/Me/2000/XP, Mac OS X and Linux). See [About OceanView Software](#).

## EEPROM Utilization

An EEPROM memory chip in each Maya2000Pro Series contains wavelength calibration coefficients, linearity coefficients, and a serial number unique to each individual spectrometer. The OOI software application reads these values directly from the spectrometer, enabling the ability to “hot-swap” spectrometers between computers without entering the spectrometer coefficients manually on each computer.

## About OceanView Software

OceanView is the latest generation of operating software for all Ocean Optics spectrometers. It is a completely modular, Java-based spectroscopy software platform that operates on Windows, Macintosh and Linux operating systems. The software can control any Ocean Optics USB spectrometer and device.

OceanView is a user-customizable, advanced acquisition and display program that provides a real-time interface to a variety of signal-processing functions. With OceanView, you have the ability to perform spectroscopic measurements (such as absorbance, reflectance, and emission), control all system parameters, collect and display data in real time, and perform reference monitoring and time acquisition experiments. Consult the OceanView manual for hardware requirements when using OceanView (see [Product-Related](#) Documentation).

## Sampling System Overview

### How Sampling Works

Ocean Optics components function in a sampling system as follows:

## 1: Introduction

---

1. The user stores reference and dark measurements to correct for instrument response variables.
2. The light transmits through an optical fiber to the sample.
3. The light interacts with the sample.
4. Another optical fiber collects and transmits the result of the interaction to the spectrometer.
5. The spectrometer measures the amount of light and transforms the data collected by the spectrometer into digital information.
6. The spectrometer passes the sample information to OOI software.
7. OOI software compares the sample to the reference measurement and displays processed spectral information.

## Modular Sampling Accessories

Ocean Optics offers a complete line of spectroscopic accessories for use with the Maya2000Pro Series. Most of our spectroscopic accessories have SMA connectors for application flexibility. Accordingly, changing the sampling system components is as easy as unscrewing a connector and replacing an accessory.

## Interface

You can use the Maya's USB connectivity with any computer that meets the following requirements:

- Microsoft Windows – Windows 2000/XP/7; 32-bit and 64-bit and Windows Vista (32-bit only)
- Apple Macintosh – OS X version 10.0 or later
- Linux – Any version released for an x86 or amd64 platform since 2010

## Shipment Components

- ❑ Maya2000Pro Series Spectrometer

The following information and documentation also ships with the Maya2000Pro Series Spectrometer:

- ❑ **Packing List**

The packing list is inside a plastic bag attached to the outside of the shipment box (the invoice arrives separately). It lists all items in the order, including customized components in the spectrometer (such as the grating, detector collection lens, and slit). The packing list also includes the shipping and billing addresses, as well as any items on back order.

- ❑ **Wavelength Calibration Data Sheet**

Each spectrometer is shipped with a Wavelength Calibration Data Sheet that contains information unique to your spectrometer. Your spectrometer operating software reads this calibration data from your spectrometer when it interfaces to a computer via the USB port.

---

**Note**

---

Please save the Wavelength Calibration Data Sheet for future reference.

---

## Other Accessories Available

Visit us at [www.OceanOptics.com](http://www.OceanOptics.com) for a complete list of products available for all of your spectroscopy needs.

- ❑ **Fibers**
- ❑ **Light Sources**
- ❑ **Integrated Sampling Systems**
- ❑ **Cuvettes**
- ❑ **Filter Holders**
- ❑ **Lithium Ion Battery Pack**
- ❑ **HR4-BREAKOUT Breakout Box**

## Breakout Box

Ocean Optics also offers the Breakout Box (HR4-BREAKOUT), a passive module that separates the signals from their 22-pin port to an array of standard connectors and headers, enabling easy access to a variety of features found in Ocean Optics' Maya2000Pro Series Spectrometer. In addition to the accessory connector, the breakout box features a circuit board based on a neutral breadboard pattern that allows custom circuitry to be prototyped on the board itself.



# Installing the Maya2000Pro Series Spectrometers

## Overview

You must install the operating software application prior to connecting your Maya2000Pro Series Spectrometer to a computer. The Ocean Optics OceanView spectrometer operating software installs the drivers required for the Maya2000Pro Series spectrometer installation. If you do not install the software first, the system will not properly recognize the Maya2000Pro Series.

If you have already connected the Maya2000Pro Series to the computer prior to installing the operating software, consult *Chapter 3: [Troubleshooting](#)* for information on correcting a corrupt Maya2000Pro Series installation.

## Maya2000Pro Series Installation

This section contains instructions for connecting the Maya2000Pro Series Spectrometer to a computer.

### ► **Procedure**

Follow the steps below to connect the Maya2000Pro Series to a computer via the USB port:

1. Install the spectrometer operating software on the destination computer.
2. Locate the USB cable (USB-CBL-1) provided with the Maya2000Pro Series Spectrometer.
3. Insert the square end of the cable into the side of the spectrometer.
4. Insert the rectangular end of the cable into the USB port of the computer.

If you installed OceanView prior to connecting the spectrometer, OceanView installs the spectrometer drivers. If the drivers do not successfully install (or if you connected the spectrometer to the computer before installing OceanView), consult *Chapter 3: [Troubleshooting](#)*.

Once you install the software and hardware, and establish your sampling system, you are ready to take measurements.

# Configuring the Maya2000Pro Series Spectrometers


The Maya2000Pro Series spectrometer can be used with OceanView software when connected to the USB port.

If you have followed the previous steps and started your software, the spectrometer is already acquiring data. Even with no light in the spectrometer, there should be a dynamic trace displayed in the bottom of the graph. If you allow light into the spectrometer, the graph trace should rise with increasing light intensity. This means the software and hardware are correctly installed.

Consult your spectrometer operating software manual for detailed instructions on operating your spectrometer (see [Product-Related Documentation](#)).

## OceanView QE Pro Acquisition Controls

In OceanView, the Acquisition Parameter Controls allow you to set the desired parameters for the Maya.




## Optional Shutter

### ► Procedure


To enable the optional shutter,



1. In the Acquisition Group window, click on the **Add/Remove Controls** tab.
2. Select **GPIO**. The GPIO controls appear on the Main Controls tab.
3. Check the **Out** box for Index 4. This makes the GPIO an output.
4. Check the **Value** box for Index 4 to close the shutter. You can now take your dark measurement.



5. Uncheck the **Value** box to open the shutter.



---

### Notes

Make sure the ALT checkbox for the GPIO (Index 4) is not selected, which would prevent the shutter from triggering.

The activation time of the internal shutter is 11 ms.

---

## Connect Spectroscopic Accessories

To find operating instructions for Maya2000Pro Series-compatible products (such as light sources, sampling chambers, and probes), consult the Ocean Optics website at <http://www.oceanoptics.com/technical/operatinginstructions.asp>.

## Change the Slit

There's no need to calibrate your spectrometer when changing the slit, just install and start measuring. There is one exception to this. You cannot change from a standard slit to a slit with a filter because it changes the optical focus and wavelength calibration of the spectrometer. In this case you would need to send the spectrometer back to Ocean Optics. A filter must be ordered for each slit (if your application requires a filter) and the spectrometer needs to be calibrated and focused with the filter installed. This only applies to filters installed inside the slit assembly.

### ► Procedure

1. Find the SMA connector. If a fiber is attached, remove it.



2. Use the Allen key to remove the 2 the screws attaching the slit to the spectrometer.
3. Pull the slit out of the spectrometer.
4. Put the new INTSMA slit connector into the spectrometer; with the key of the connector on the left side.



5. Install the 2 screws again. Use the Allen key to tighten the screws carefully (do not over-tighten).
6. If necessary, connect the fiber again.



# Troubleshooting

## Overview

The following sections contain information on troubleshooting issues you may encounter when using the Maya2000Pro Series Spectrometer.

## Maya2000Pro Series Spectrometers Connected to Computer Prior to Software Installation

### Windows Operating Systems

If you connected your Ocean Optics Maya2000Pro Series device to the computer prior to installing your OceanView spectrometer operating software application on a Windows platform, you may encounter installation issues that you must correct before your Ocean Optics device will operate properly.

Follow the applicable steps below to remove the incorrectly installed device, device driver, and installation files.

---

#### Note

If these procedures do not correct your device driver problem, you must obtain the *Correcting Device Driver Issues* document from the Ocean Optics website:  
<http://www.oceanoptics.com/technical/engineering/correctingdevicedriverissues.pdf>.

---

### Remove the Unknown Device from Windows Device Manager

#### ► Procedure

1. Open Windows Device Manager. Consult the Windows operating instructions for your computer for directions, if needed.
2. Locate the **Other Devices** option and expand the **Other Devices** selection by clicking on the "+" sign to the immediate left.

### Note

Improperly installed USB devices can also appear under the Universal Serial Bus Controller option. Be sure to check this location if you cannot locate the unknown device.

---

3. Locate the unknown device (marked with a large question mark). Right-click on the **Unknown Device** listing and select the **Uninstall** or **Remove** option.
4. Click the **OK** button to continue. A warning box appears confirming the removal of the Unknown Device. Click the **OK** button to confirm the device removal.
5. Disconnect the Maya2000Pro Series from your computer.
6. Plug in the spectrometer.

The system is now able to locate and install the correct drivers for the USB device.

## Mac Operating Systems

Since there are no device files for the Maya2000Pro Series Spectrometer in a Mac operating system, you should not encounter any problems if you installed the spectrometer before the OceanView software.

## Linux Operating Systems

For Linux operating systems, all you need to do is install the OceanView software, then unplug and replug in the spectrometer. Technically, the driver files for Linux simply give nonprivileged users permission to use newly connected hardware. There isn't any long-term harm to plugging in the device before installing the software.

---

## Appendix A

# Calibrating the Wavelength of the Maya2000Pro Series Spectrometers

## Overview

This appendix describes how to calibrate the wavelength of your spectrometer. Though each spectrometer is calibrated before it leaves Ocean Optics, the wavelength for all spectrometers will drift slightly as a function of time and environmental conditions. Ocean Optics recommends periodically recalibrating the Maya2000Pro Series.

## About Wavelength Calibration

You are going to be solving the following equation, which shows that the relationship between pixel number and wavelength is a third-order polynomial:

$$\lambda_p = I + C_1p + C_2p^2 + C_3p^3$$

Where:

$\lambda$  = the wavelength of pixel  $p$

$I$  = the wavelength of pixel 0

$C_1$  = the first coefficient (nm/pixel)

$C_2$  = the second coefficient (nm/pixel<sup>2</sup>)

$C_3$  = the third coefficient (nm/pixel<sup>3</sup>)

You will be calculating the value for  $I$  and the three  $C$ s.

# Calibrating the Spectrometer

## Preparing for Calibration

To recalibrate the wavelength of your spectrometer, you need the following components:

- A light source capable of producing spectral lines

---

### Note

Ocean Optics' HG-1 Mercury-Argon lamp is ideal for recalibration. If you do not have an HG-1, you need a light source that produces several (at least 4-6) spectral lines in the wavelength region of your spectrometer.

- A Maya2000Pro Series spectrometer
- An optical fiber (for spectrometers without a built-in slit, a 50- $\mu\text{m}$  fiber works best)
- A spreadsheet program (Excel or Quattro Pro, for example) or a calculator that performs third-order linear regressions

---

### Note

If you are using Microsoft Excel, choose **Tools | Add-Ins** and check **AnalysisToolPak** and **AnalysisToolPak-VBA**.

## Calibrating the Wavelength of the Spectrometer

### ► Procedure

Perform the steps below to calibrate the wavelength of the spectrometer:

1. Place the spectrometer operating software into Scope mode and take a spectrum of your light source. Adjust the integration time (or the A/D conversion frequency) until there are several peaks on the screen that are not off-scale.
2. Move the cursor to one of the peaks and position the cursor so that it is at the point of maximum intensity.
3. Record the pixel number that is displayed in the status bar or legend (located beneath the graph). Repeat this step for all of the peaks in your spectrum.
4. Use the spreadsheet program or calculator to create a table like the one shown in the following figure. In the first column, place the exact or true wavelength of the spectral lines that you used.

In the second column of this worksheet, place the observed pixel number. In the third column, calculate the pixel number squared, and in the fourth column, calculate the pixel number cubed.



Independent Variable	Dependent Variables			Values Computed from the Regression Output	
True Wavelength (nm)	Pixel #	Pixel # <sup>2</sup>	Pixel # <sup>3</sup>	Predicted Wavelength	Difference
253.65	175	30625	5359375	253.56	0.09
296.73	296	87616	25934336	296.72	0.01
302.15	312	97344	30371328	302.40	-0.25
313.16	342	116964	40001688	313.02	0.13
334.15	402	161604	64964808	334.19	-0.05
365.02	490	240100	117649000	365.05	-0.04
404.66	604	364816	220348864	404.67	-0.01
407.78	613	375769	230346397	407.78	0.00
435.84	694	481636	334255384	435.65	0.19
546.07	1022	1044484	1067462648	546.13	-0.06
576.96	1116	1245456	1389928896	577.05	-0.09
579.07	1122	1258884	1412467848	579.01	0.06
696.54	1491	2223081	3314613771	696.70	-0.15
706.72	1523	2319529	3532642667	706.62	0.10
727.29	1590	2528100	4019679000	727.24	0.06
738.40	1627	2647129	4306878883	738.53	-0.13
751.47	1669	2785561	4649101309	751.27	0.19

- Use the spreadsheet or calculator to calculate the wavelength calibration coefficients. In the spreadsheet program, find the functions to perform linear regressions.
  - If using Quattro Pro, look under **Tools | Advanced Math**
  - If using Excel, look under **Analysis ToolPak**
- Select the true wavelength as the dependent variable (Y). Select the pixel number, pixel number squared, and the pixel number cubed as the independent variables (X). After executing the regression, you will obtain an output similar to the one shown below. Numbers of importance are noted.

**Regression Statistics**

Multiple R 0.999999831  
 R Square 0.999999663 ← R Squared  
 Adjusted R Square 0.999999607  
 Standard Error 0.125540214  
 Observations 22

	<u>Coefficients</u>	<u>Standard Error</u>	
Intercept	190.473993	0.369047536	← First coefficient
X Variable 1	0.36263983	0.001684745	
X Variable 2	-1.174416E-05	8.35279E-07	
X Variable 3	-2.523787E-09	2.656608E-10	← Second coefficient

↑ Third coefficient

7. Record the Intercept, as well as the First, Second, and Third Coefficients. Additionally, look at the value for R squared. It should be very close to 1. If not, you have most likely assigned one of your wavelengths incorrectly.

Keep these values at hand.

## Saving the New Calibration Coefficients: USB Mode

Ocean Optics programs wavelength calibration coefficients unique to each Maya2000Pro Series Spectrometer onto an EEPROM memory chip in the spectrometer.

You can overwrite old calibration coefficients on the EEPROM using the Maya2000Pro Series Spectrometer via the USB port.

### ► **Procedure**

To save wavelength calibration coefficients using the USB mode, perform the following steps:

1. Ensure that the Maya2000Pro Series is connected to the PC and that you have closed all other applications.
2. Point your browser to <http://www.oceanoptics.com/technical/softwaredownloads.asp> and scroll down to **Microcode**. Select **USB EEPROM Programmer**.
3. Save the setup file to your computer.
4. Run the **Setup.exe** file to install the software. The **Welcome** screen appears.
5. Click the **Next** button. The **Destination Location** screen appears.
6. Accept the default installation location, or click the **Browse** button to specify a directory. Then, click the **Next** button. The **Program Manager Group** screen appears.
7. Click the **Next** button. The **Start Installation** screen appears.
8. Click the **Next** button to begin the installation. Once the installation finishes, the **Installation Complete** screen appears.
9. Click the **Finish** button and reboot the computer when prompted.
10. Navigate to the **USB EEPROM Programmer** from the Start menu and run the software.
11. Click on the desired spectrometer displayed in the left pane of the **USB Programmer** screen.
12. Double-click on each of the calibration coefficients displayed in the right pane of the USB Programmer screen and enter the new values acquired in Steps 5 and 6 of the [Calibrating the Wavelength of the Spectrometer](#) section in this appendix.
13. Repeat Step 12 for all of the new values.
14. Click on the **Save All Values** button to save the information, and then **Exit** the USB Programmer software.

The new wavelength calibration coefficients are now loaded onto the EEPROM memory chip on the Maya2000Pro Series Spectrometer.

---

# Appendix B

# Specifications

## Overview

This appendix contains information on spectrometer operation, specifications, and system compatibility. It also includes accessory connector pinout diagrams and pin-specific information.

## How the Maya2000Pro Series Works

The optical bench has no moving parts that can wear or break; all the components are fixed in place at the time of manufacture.



## Maya2000Pro Series Components Table

Ocean Optics permanently secures all components in the Maya2000Pro Series Spectrometers at the time of manufacture. Only Ocean Optics technicians can replace interchangeable components, where noted.

Item	Name	Description
1	SMA Connector	Secures the input fiber to the spectrometer. Light from the input fiber enters the optical bench through this connector.
2	Slit	<p>A dark piece of material containing a rectangular aperture, which is mounted directly behind the SMA Connector. The size of the aperture regulates the amount of light that enters the optical bench and controls spectral resolution.</p> <p>You can also use the Maya2000Pro Series Spectrometer without a Slit. In this configuration, the diameter of the fiber connected to the spectrometer determines the size of the entrance aperture.</p> <p>Only Ocean Optics technicians can change the Slit.</p>
3	Filter	<p>Restricts optical radiation to pre-determined wavelength regions. Light passes through the Filter before entering the optical bench. Both bandpass and longpass filters are available to restrict radiation to certain wavelength regions.</p> <p>Only Ocean Optics technicians can change the Filter.</p>
4	Collimating Mirror	<p>Focuses light entering the optical bench towards the Grating of the spectrometer. Light enters the spectrometer, passes through the SMA Connector, Slit, and Filter, and then reflects off the Collimating Mirror onto the Grating.</p>
5	Grating	<p>Diffraction light from the Collimating Mirror and directs the diffracted light onto the Focusing Mirror. Gratings are available in different groove densities, allowing you to specify wavelength coverage and resolution in the spectrometer.</p> <p>Only Ocean Optics technicians can change the Grating.</p>
6	Focusing Mirror	Receives light reflected from the Grating and focuses the light onto the CCD Detector or L2 Detector Collection Lens (depending on the spectrometer configuration).
7	Detector with OFLV Filter	Eliminates second-order effects and is used with an HC-1 Grating in a 200-950 nm wavelength system in a Maya2000Pro Series spectrometer.
8	Back-thinned Area Detector	<p>Provides 90% (Maya200) or 75% (Maya2000Pro Pro) quantum efficiency and bins pixels in a vertical column to acquire light from the entire height of the spectrometer's slit image. This improves light collection and signal-to-noise significantly. This 2D area detector is back-thinned (back-illuminated) and does not require the detector upgrade that is normally applied to other detectors.</p> <p>Only Ocean Optics technicians can add or remove the Detector.</p>

# Maya2000Pro Series Spectrometers Specifications


The following sections provide specification information for the CCD detector in the Maya2000Pro Series spectrometers, as well as for each model Maya2000Pro Series Spectrometer itself.

## CCD Detector Specifications

Specification	Maya2000 Pro	Maya2000Pro-NIR
Detector	Hamamatsu S10420, back-thinned FFT-CCD	Hamamatsu S11510, back-thinned FFT-CCD
Thermoelectric cooling	No	
Number of pixels	All: 2068 x 70 Active: 2048 x 64	
Spectral range	200-1100 nm with window, Deep UV option available (150nm). Deep UV option includes purge port and window removal. 175-1100 nm with HC1 grating.	
Pixel size	14 $\mu$ m square	
Pixel well depth	200 Ke-	
Column height	896 $\mu$ m square	
Detector active area (mm)	28.672 horizontal x 0.896 vertical	
Quantum efficiency: Peak QE QE @ 250 nm	75% at 600 nm 60%	85% at 700 nm

## B: Specifications

■ Spectral response (without window)\*1



\*1: Spectral response with quartz glass is decreased according to the spectral transmittance characteristic of window material.

### Quantum Efficiency of S10420 and S11510 Detectors

## Maya2000Pro Series Spectrometer Specifications

Specification	Maya2000 Pro	Maya2000Pro-NIR
Dimensions (LxWxH)	148.6 mm (5.85 in.) x 109.3 mm (4.30 in.) x 50.4 mm (1.98 in.)	
Weight	0.96 kg (2.12 lbs.)	
Temperature Operation Storage	-0 °C to +50 °C -30 °C to +70 °C	
Humidity	0 – 90% noncondensing	
Power consumption	500 mA @ 5 VDC	
Supply Voltage	4.5 – 5.5 V	
Power-up Time	~ 2s depending on code size	
Gratings	14 gratings available	
Entrance aperture	5, 10, 25, 50, 100 or 200 µm wide slits	
Order-sorting filters	6 OF series available	
Focal length (input)	f/4, 101 mm	
Optical resolution (FWHM)	Depends on grating and size of entrance aperture	
A/D converter	16 bit, 150 kHz+	

Specification	Maya2000 Pro	Maya2000Pro-NIR
Dynamic range Spec Typical		8000:1 12000:1+
Signal-to-noise ratio		450:1
Non-linearity Uncorrected Corrected		~10.0% <1.0%
Fiber optic connector	SMA 905 to single-strand optical fiber (0.22 NA)	
Integration time	6 ms to 5 seconds	
Interfaces	USB 2.0	

## System Compatibility

You can use the Maya2000Pro Series' USB connectivity with any computer that meets the requirements for the spectrometer operating software being used (Windows, Mac OS X and Linux). See [About OceanView Software](#).

## 30-Pin Accessory Connector Pinout


The Maya2000Pro Series features a 30-pin Accessory Connector, located on the side of the unit as shown:



Location of Maya2000Pro Series 30-Pin Accessory Connector

## 30-Pin Accessory Connector Pinout Diagram

When facing the 30-pin Accessory Connector on the front of the vertical wall of the Maya2000Pro Series Spectrometer, pin numbering is as follows:



30-Pin Accessory Connector Pinout Diagram

## 30-Pin Accessory Connector – Pin Definitions and Descriptions

The following table contains information regarding the function of each pin in the Maya2000Pro Series Spectrometer’s 30-Pin Accessory Connector:

Pin #	Function	Input/Output	Description
1	N/A	N/A	Reserved
2	N/A	N/A	Reserved



Pin #	Function	Input/Output	Description
3	GPIO (2)	Input/Output	General purpose software-programmable, digital input/output (channel number)
4	N/A	N/A	Reserved
5	Ground	Input/Output	Ground
6	I <sup>2</sup> C SCL	Input/Output	I <sup>2</sup> C clock signal for communication to other I <sup>2</sup> C peripherals
7	GPIO (0)	Input/Output	General purpose software-programmable, digital input/output (channel number)
8	I <sup>2</sup> C SDA	Input/Output	I <sup>2</sup> C data signal for communication to other I <sup>2</sup> C peripherals
9	GPIO (1)	Input/Output	General purpose software-programmable, digital input/output (channel number)
10	Ext. Trigger In	Input	TTL input trigger signal
11	GPIO (3)	Input/Output	General purpose software-programmable, digital input/output (channel number)
12	V <sub>CC</sub> or 5V <sub>IN</sub>	Input or Output	Input power pin for Maya2000Pro Series – When operating via USB, this pin can power other peripherals – Ensure that peripherals comply with USB specifications (no TEC power)
13	SPI Data Out	Output	SPI Master Out Slave In (MOSI) signal for communication to other SPI peripherals
14	V <sub>CC</sub> or 5V <sub>IN</sub>	Input or Output	Input power pin for Maya2000Pro Series – When operating via USB, this pin can power other peripherals – Ensure that peripherals comply with USB specifications (no TEC power)
15	SPI Data In	Input	SPI Master In Slave Out (MISO) signal for communication to other SPI peripherals
16	GPIO (4)	Input /Output	General purpose software-programmable, digital input/output (channel number). Controls the optional shutter.
17	Single Strobe	Output	TTL output pulse used as a strobe signal – Has a programmable delay relative to the beginning of the spectrometer integration period
18	GPIO (5)	Input/Output	General purpose software-programmable, digital input/output (channel number)
19	SPI Clock	Output	SPI clock signal for communication to other SPI peripherals
20	Continuous	Output	TTL output signal used to pulse a strobe – Divided down from

## B: Specifications

Pin #	Function	Input/Output	Description
	Strobe		the master clock signal
21	SPI Chip Select	Output	SPI Chip/Device Select signal for communication to other SPI peripherals
22	GPIO (6)	Input/Output	General purpose software-programmable, digital input/output (channel number)
23	N/A	N/A	Reserved
24	N/A	N/A	Reserved
25	Lamp Enable	Output	TTL signal driven Active HIGH when the Lamp Enable command is sent to the spectrometer
26	GPIO (7)	Input/Output	General purpose software-programmable, digital input/output (channel number)
27	Ground	Input/Output	Ground
28	GPIO (8)	Input/Output	General purpose software-programmable, digital input/output (channel number)
29	Ground	Input/Output	Ground
30	GPIO (9)	Input/Output	General purpose software-programmable, digital input/output (channel number)

## 30-Pin J2 Accessory Connector - Part Numbers

The part numbers for the 30-pin accessory connector on the Maya2000Pro Series Spectrometer are as follows:

- The connector is Pak50™ model from 3M Corp. Headed Connector – Part Number **P50-030P1-RR1-TG**.
- The mating connector is Part Number **P50-030S-TGF**.
- Mating the two components requires two 1.27 mm (50 mil) flat ribbon cables (3M 3365 Series is recommended).

---

# Index

## 3

30-pin accessory connector  
  diagram, 24  
  part numbers, 26  
  pin definitions, 24

## A

accessories, 5, 10  
Accessories, 4  
accessory connector  
  pinout, 23  
Acquisition Controls  
  OceanView, 8

## B

breakout box, 5

## C

Calibrating, iii, 15  
calibration, 15  
  preparing for, 16  
  procedure, 16  
calibration coefficients  
  saving in USB mode, 18  
CCD, 21  
collimating mirror, 20  
compatibility, 23  
Components Table, 20  
configuring in OceanView  
  TE Cooler, 8

## D

detector, 21  
document  
  audience, iii  
  purpose, iii

summary, iii

## E

EEPROM, 3

## F

filter, 20  
focusing mirror, 20

## G

grating, 20

## I

Installation, 7  
installed filter, 20  
Interface, 4  
ISO certification, iv

## M

memory chip, 3  
mirror, 20

## O

OceanView, 3  
  Acquisition Controls, 8

## P

packing list, 4  
power supply (external), 22  
product-related documentation, iii

**S**

Sampling  
  Accessories, 4  
  System, 3  
setup, 7  
shipment components, 4  
shutter control, 8  
slit, 20  
  change, 10  
SMA Connector, 20  
software  
  OceanView, 3  
specifications, 19  
  detector, 21  
  spectrometer, 22  
specifications, 21  
spectroscopic accessories, 10  
System Requirements, 3

**T**

TE Cooler, 8  
troubleshooting  
  Linux systems, 14  
  Mac systems, 14  
Troubleshooting, 13

**U**

upgrades, iv

**W**

Wavelength Calibration  
  about, 15  
Wavelength Calibration Data File, 4  
Wavelength Calibration Data Sheet, 4  
what's new, iii